

Displaying parts and ports

- [Ways to display parts and ports](#)
 - [Using the Display Parts/Ports dialog](#)
 - [Using the diagram toolbar and the shortcut menu](#)
 - [Using the smart manipulator toolbar](#)
 - [Using the drag-and-drop operation in the SysML Internal Block diagram](#)
- [Displaying properties of a port](#)

You can display ports, properties, and deep nested parts and properties that have already been created in all [structure diagrams](#). This functionality is driven by stereotypes, which allow you to display properties [stereotypes](#) have been applied to. If you have applied your own [stereotypes](#) for the elements (e.g., electrical, mechanical, optical), you can use those stereotypes when selecting the properties you want to display on the diagram pane.



Note

For more information about creating custom stereotypes and applying them, see [UML Profiling and DSL Guide](#).

This page contains the following information:

- [Ways to display parts and ports](#)
 - [Using the Display Parts/Ports dialog](#)
 - [Using the diagram toolbar and the shortcut menu](#)
 - [Using the smart manipulator toolbar](#)
 - [Using the drag-and-drop operation in the SysML Internal Block diagram](#)
- [Displaying properties of a port](#)

Ways to display parts and ports

You can display ports and properties in the following ways:

- [Using the Display Parts/Ports dialog](#)
- [Using the diagram toolbar and the shortcut menu](#)
- [Using the smart manipulator toolbar](#)
- [Using the drag-and-drop operation in the SysML Internal Block diagram](#)


Using the Display Parts/Ports dialog

You can use the **Display Parts/Ports** dialog to control how much of a structure should be displayed. The **Display Parts/Ports** dialog opens automatically when creating a new [SysML Internal Block diagram](#) for a [Block](#) element that owns ports and properties. It can also be accessed and opened in the structure diagrams that have already been created. The **Display Parts/Ports** dialog allows you to:

- Preview all [parts](#), ports, and other properties in one place.
- Manually or automatically select the required parts, ports, and other properties you want to display.
- Manually or automatically choose the deeply [nested](#) parts, ports, and other properties you want to display.
- Define layout options for parts.
- Specify layout options for ports.





The **Display Parts/Ports** dialog consists of the following areas:


- *Dialog toolbar* allows you to show or hide additional information about listed elements.
- *Element tree* displays all owned internal structure of a context [Block](#).
- *Panel* is a context-sensitive area that depends on the selected property from the Element tree. It allows you to batch select parts/ports in the Element tree. You can select all, clear all, or choose properties only by type, stereotype, or aspect.
- *Options* area allows you to choose the layout of the selected parts and ports when they appear in the diagram.



The following procedure will guide you in working with the **Display Parts/Ports** dialog when you want to display required ports and properties on the diagram pane.

To display ports and properties using the **Display Parts/Ports** dialog

1. Open the **Display Parts/Ports** dialog:
 - When creating a new [SysML Internal Block diagram](#), the dialog opens automatically.
 - When editing an already created [structure diagram](#), the dialog can be opened in the following ways:
 - Select either a diagram frame or single/multiple element shapes. On the diagram toolbar, click  and choose **Display Parts/Ports**.
 - Right-click either a diagram frame or single/multiple element shapes, and select **Display > Display Parts/Ports**.
2. (Optional) Enable buttons from the **Display Parts/Ports** dialog toolbar if you want to show or hide additional information about listed elements:
 - Click  to show the full path of elements.
 - Click  to show the full types of elements.
 - Click  to show the inherited elements.

- Click  to show the inherited properties.

3. Choose the properties you want to display, using one or more of the following methods:

Warning
If certain check boxes are inactive in the element list, those elements are already displayed in the diagram.

- Use the element tree located on the left side of the dialog:
 - Manually select individual check boxes one by one.
 - Select recursively nested elements by holding down the Shift key while selecting the corresponding check box for the element.

Example 1


All properties (in this example all ports *AirFlowPort*, *ElectricityPort*, *AutomotiveBusesPort*) of the *Air Distribution* Part Property are selected recursively by holding down the Shift key while selecting the corresponding check box from the element tree in the **Display Parts/Ports** dialog.

- Use the context-sensitive panel located on the right side of the dialog:
 - **Select Properties** group - displays all property types (including your own stereotypes) that are owned by the selected element from the element tree located on the left side of the dialog.
 - **Select Ports** group - displays all port types (including your own stereotypes) that are owned by the selected element from the element tree located on the left side of the dialog.

Example 2

All Electrical ports (in this example only one *ElectricityPort* port) of the *Data Transfer* Part Property are selected in the element tree by using the **Select Ports** group in the context-sensitive panel of the **Display Parts/Ports** dialog.

4. Specify the
- Pa
 - Us
 - bo
 - au
 - Sh
 - T



5. Click **OK**.

After those steps, all

Using the diagram

In the structure diagram

- The **Display**
- The **Display**

You can also use the interactive and dependency menu. In the diagram pane, the menu contains only the commands that can be applied to the selected Part Property shape. If you select nothing in the diagram pane, the menu shows commands that can be applied to the whole diagram.

These commands under the **Display** button and shortcut menu are comprised of elements that are still not displayed on the diagram according to their:

- Metatypes.
- Stereotypes.
- Types stereotypes.


The following procedures will show you how to:

- [How to display Ports, Properties using the **Display** button.](#)
- [How to display Ports, Properties using the shortcut menu.](#)
- [How to hide Ports.](#)

To display ports, properties using the **Display** button

1. Select either a diagram frame or single/multiple element shapes.

2. On the diagram toolbar, click



3. From the opened command menu, select required properties or ports to display:
 - All ports that are available to display are listed under the **Display Ports** command group.

Important

If nothing is selected on the diagram pane, the **Display Ports** command group will contain commands that allow you to display two levels of structure: ports are displayed on the diagram frame and on the first level parts.


- All properties that are available to display are listed under the **Display Properties** command group.

After selecting the required command from the **Display** button, the appropriate properties are displayed on the diagram pane.

To display ports, properties using the shortcut menu

1. Right-click either the diagram pane or single/multiple element shapes.

- From the shortcut menu, select the **Display** command group.




- From the opened command menu, select required properties to display:
 - All Ports that are available to display are listed under the **Display Ports** command group.

Important

Nothing is selected on the diagram pane, the **Display Ports** command group allows you to display two levels of structure: ports are displayed on the diagram frame and on the first-level parts.

- All Properties that are available to display are listed under the **Display Properties** command group.
After selecting the required command from the **Display** command menu, the appropriate properties' ports are displayed on the diagram pane.


To hide ports

- Select either a diagram pane or any number of element shapes. On the diagram toolbar, click  and choose **Hide All Ports**.
- Right-click either a diagram pane or any number of element shapes, and select **Display > Hide All Ports**.
After selecting the command, the ports of the selected shape will be hidden from the diagram pane, but not removed from the model.


Warning

If the **Hide All Ports** command doesn't appear, the selection or diagram doesn't contain any ports that can be hidden.

Before hiding all ports




After hiding all ports



Using the smart manipulator toolbar

When the properties are already displayed on the [structure diagrams](#), you can display their direct ports using the **Display All Ports** button from the smart manipulator toolbar. It only allows you to display first level ports, and does not allow you to display deeply nested ports. To display deeply nested ports, you should use the **Display Parts/Ports** dialog. The steps below show how to display ports of a selected property shape.


To display Ports on shapes

1. Select the required element shape or a diagram frame.
 2. From the smart manipulator toolbar, click .
- All first level Ports of the selected shape will be displayed on the diagram pane.



Warning

If the **Display All Ports** button is not available, the selected element or diagram doesn't own any Port.



Using the drag-and-drop operation in the SysML Internal Block diagram

The most efficient way to create a new [Part Property](#) and display it with all ports in the [SysML Internal Block diagram](#) is by dragging the [Block](#) or [Property](#) elements. This method only allows you to display first level properties, and does not allow you to display deeply nested properties. To display deeply nested elements, use the **Display Parts/Ports** dialog. The following procedures will show you:

- [How to create a Part Property shape and how to display all its ports when dragging the Block element.](#)
- [How to display a Part Property shape and all its ports by dragging the Part Property element.](#)

You can create a new [Part Property](#) by dragging the [Block](#) element from the [Model Browser](#) to the [SysML Internal Block diagram](#) pane. The newly created [Part Property](#) will be typed by the dragged [Block](#) and displayed on the diagram pane. If this [Block](#) has ports defined, you can display them by using the long drag, and selecting an appropriate option from the opened menu (see Example 3).

To create and display a [Part Property](#) by dragging a [Block](#) element

- Drag a single or a multiple [Block](#) element from the [Model Browser](#) onto the diagram pane.
- Drag a single or a multiple [Block](#) element from the [Model Browser](#) onto the diagram pane, and hold it down until the Tooltip appears (long drag). Drop it, and, from the opened menu, select the **Create Property Symbol** command. The new [Part Property](#) is created in the model, and displayed on the [diagram pane](#). The newly created [Part Property](#) is typed by the dragged [Block](#) automatically.

To create and display a [Part Property](#) and display all its ports by dragging a [Block](#) element

- Drag a single or a multiple [Block](#) element from the [Model Browser](#) onto the [diagram pane](#), and hold it down until the Tooltip appears (long drag).
- Drop it, and, from the opened menu, select the **Create Property Symbol and Display All Ports** command. The new [Part Property](#) is created in the model, and displayed with all its ports on the diagram pane. The newly created [Part Property](#) is typed by the dragged [Block](#) automatically.



Tip

After creating an element, it is beneficial to find its location in the model tree by performing one of the following:

- Right-click the shape, and, from the shortcut menu, choose the **Select in Containment Tree** command.
- Select the shape and press Alt+B.



Example 3

You can display a [Part Property](#) shape by dragging a [Part Property](#) element from the [Model Browser](#) to the [SysML Internal Block diagram](#) pane. If this [Part Property](#) has ports defined, you can display them by using the long drag, and selecting an appropriate option from the opened menu (see Example 4).

The following procedures describe how to display [Part Property](#) shape and all its ports by dragging the [Part Property](#) element.

To display a [Part Property](#) shape by dragging a [Part Property](#) element

- Drag a single or a multiple [Part Property](#) element from the [Model Browser](#) onto the [diagram pane](#).
- Drag a single or a multiple [Part Property](#) element from the [Model Browser](#) onto the [diagram pane](#), and hold it down until the Tooltip appears (long drag). Drop it, and, from the opened menu, select the **Create Part Property Symbol** command. The [Part Property](#) shape is displayed on the diagram pane.

To display a [Part Property](#) with all of its ports by dragging a [Part Property](#) element

- Drag a single or a multiple [Part Property](#) element from the [Model Browser](#) onto the [diagram pane](#), and hold it down until the Tooltip appears (long drag).
- Drop it, and, from the opened menu, select the **Create Part Property Symbol and Display All Ports** command. The [Part Property](#) shape is displayed with all its ports on that shape.






Example 4

After completing the steps outlined above, the [Part Property](#) shape and/or all its ports are displayed on the [SysML Internal Block diagram](#).

Displaying properties of ports and displaying all ports

If you display the properties of a port, all properties of its type will be displayed inside the port shape and Part Property compartments will be enabled for that port.





Related pages

- [Applying Stereotypes](#)
- [Nesting parts that are association ends](#)
- [Mapping ports on a Part type change](#)
- [Proxy Port](#)
- [Full Port](#)
- [Flow Port](#)
- [Displaying elements](#)
- [SysML Internal Block Diagram](#)
- [Autowiring](#)
- [Connecting Parts Through Interface](#)
- [Enforce Ports Compatibility mode](#)
- [Hiding direction arrow on Port shape](#)
- [Property path notation](#)

Sample model

The models used in the figures of this page are:

- The **Vehicle Climate Control Unit** sample model. To open this sample download [Vehicle Climate Control Unit.mdzip](#).
- The **Vehicle parts under ports** sample model. To open this sample download [Vehicle parts under ports.mdzip](#).